

CLAIMS

1. Circuit to reduce the variations of the auto-supply voltage (V_{cc}) of a control circuit (12) of a switching power supply where said control circuit (12) supplies an activation or deactivation signal for a power transistor comprising: a generator (W_a) of said auto-supply voltage (V_{cc}); characterised in that it comprises a controlled switch (T) capable of selectively connecting said generator (W_a) to said control circuit (12); and a driving circuit (SW2) of said controlled switch (T) that supplies a closing signal of said controlled switch (T) after a predefined time delay (T_d) starting from said deactivation command.

2. Circuit in accordance with claim 1 characterised in that it comprises a circuit generator (I_{ch} , C, SW1) that generates said predefined time delay.

3. Circuit in accordance with claim 1 characterised in that said circuit generator (I_{ch} , C, SW1) generates said predefined time delay proportionally to a voltage (V_{comp}) proportional to the load of said switching power supply.

4. Circuit in accordance with claim 1 characterised in that it comprises a first comparator (COM1) that compares a voltage (V_{comp}) proportional to the load of said switching power supply with a first reference voltage (V_{t1}), said predefined time delay (T_d) is substantially nil when said voltage (V_{comp}) proportional to the load of said switching power supply is lower than said first reference voltage (V_{t1}).

5. Circuit in accordance with claim 1 characterised in that it comprises a second comparator (COM2) that compares a voltage (V_{comp}) proportional to the load of said switching power supply with a second reference voltage (V_{t2}), said controlled switch (T) remains open when said voltage (V_{comp}) proportional to the load of said switching power supply is higher than said second reference voltage (V_{t2}).

6. Circuit in accordance with claim 1 characterised in that said drive circuit (12) of said controlled switch (T) supplies an opening signal of said

- 15 -

controlled switch (T) starting from said activation command.

7. Switching power supply comprising a circuit for reducing the variations of the auto-supply voltage of the control circuit of a switching power supply in accordance with claim 1.

5 8. Method for reducing the variations of the auto-supply voltage (V_{cc}) of a control circuit (12) of a switching power supply where said control circuit (12) supplies an activation or deactivation command signal of a power transistor characterised in that it selectively connects the secondary of the transformer (W_a) of said switching power supply to said control circuit
10 (12) after a predefined delay of time (T_d) starting from said deactivation command.